BExCBG05-05 Explosion Proof Dual Xenon Beacon 5 Joule



The flameproof BExCBG05-05 dual Xenon beacons are suitable for Zone 1, 2, 21 & 22 applications. Approved to IECEx, ATEX and Ex EAC standards.

The BExCBG05-05D dual 5 Joule beacons robust construction enables installation in the harshest of environments. The beacons may be connected from a single supply for simultaneous operation or from separate supplies for independent operation. Additional features include automatic synchronisation on multi-beacon systems and stainless steel guard and mounting bracket as

The BEx range features enclosures manufactured from corrosion proof, marine grade copper free LM6 aluminium with a chromate and powder coat finish. All models have two M20 cable entries, large termination areas containing in & out terminals and an ingress protection of IP66/67.

Features

- Marine grade, corrosion proof, LM6 aluminium enclosure
- Automatic synchronisation on multi-beacon system.
- Beacons can be set to 'flip-flop' alternating mode with other units on multi-beacon systems.
- Xenon tubes mechanically secured against shock & vibration
- Glass lens & Stainless Steel guard
- Very large termination area.
- Dual M20 cable entries adaptors available.
- Stopping plug included.
- Ratchet adjustable stainless steel 'U' bracket.
- Reverse polarity diode fitted.
- IP66/67 ingress protection.
- 120+120 candela effective light intensity.
- UV stable PC, field replaceable, colour lens filters.

Approvals

• IECEx KEM 10.0024X

IEC 60079-0:2011 IEC 60079-1: 2007-4 IEC 60079-31:2013

ATEX KEMA 00ATEX2222X

EN 60079-0: 2012 + A11 EN 60079-1:2007 EN 60079-31:2014

• TR-CU Ex EAC certificate: RU C-G B.AA71.B.00109

Coding

- II 2G Ex d IIB T4 Gb Ta. -50°C to +70°C
- II 2D Ex tb IIIC T115°C Db Ta. -50°C to +55°C
- II 2D Ex tb IIIC T130°C Db Ta. -50°C to +70°C




















Specification

Energy:	5 Joules x 2 (5Ws)	
Flash rate:	1Hz (60 fpm)	
Peak Candela:	500,000 cd x2 - calculated from energy (J)	
Eff. Intensity cd:	250 cd x2 - calculated from energy (J)	
Peak Candela:	39,463 cd* x2 - measured ref. to I.E.S.	
Eff. Intensity cd:	120 cd* x2 - measured ref. to I.E.S.	
Lens colours:	Amber, Blue, Clear, Green, Magenta, Red & Yellow	
Voltages DC:	12 vdc; 2 4vdc; 48vdc	
Voltages AC:	115vac; 230vac	
Ingress protection:	IP66/67	
Enclosure matl:	Marine grade copper free LM6 Aluminium	
Enclosure finish:	Chromate & powder coated finish - anti-corrosion.	
Colour:	RAL 3000 Red (others available on request)	
Cable entries:	Dual M20ISO (one stopping plug inc)	
Terminals:	0.5 - 2.5mm² (20-14 AWG)	
Enclosure volume:	✓ litres	
Line monitoring:	Blocking diode included EOL Min. 500 Ohm 2w, or 3k3 Ohm 0.5w resistor or diode (DC versions) can be fitted	
Grounding stud:	M5	
Temperature range:	-50° to +70°C (-58°F to +158°F)	
Relative humidity:	90% at 20°C [68°F]	
Tube life:	Emissions are reduced to 70% after 8 million flashes	
Weight:	DC: 4.00kg/8.8lbs AC: 4.35kg/9.57lbs	
* * * * * * * * * * * * * * * * * * * *		

^{*}All candela data is representative of performance with clear lens at optimum voltage.

Part Codes

rait codes				
Version: Product type:	Part code: BExCBG 0505	Explosion proof Dual 5J Xenon Beacon		
Туре:	DP	Ex d, UV stable PC Colour Lenses		
Voltage:	DC024 AC115 AC230	2 4V dc 115V ac 2 40V ac		
Cable Entry Type: [e] Note:	A B C D E F G	2 x M2 0x1.5mm 2 x 1/2" NPT - adaptors 2 x 3/4" NPT - adaptors 2 x M2 5x1.5mm - adaptors 1 x 1/2" NPT - adaptor 1 x 3/4" NPT - adaptor 1 x M2 5x1.5mm - adaptor M20 stopping plugs for unused en	ntrie	es supplied
Adaptor/Stopping plug material: [m]	B N S	Brass Nickel Plated Stainless Steel		
Bracket/guard matl: [s]	1 2 3 4	A2 304 Stainless Steel A4 316 Stainless Steel A2 304 St/St with Equip. Tag A4 316 St/St with Equip. Tag (304)		
Product version: [v]	A1	Default - IECEx, ATEX		
Enclosure colour: [x]	R S	Red RAL3000 Special - contact E2S		
1st Xenon lens colour: [y] 2 nd Xenon lens colour: [y]	A B C G M R	Amber Blue Clear G reen Magenta Red	B C G M R	Amber Blue Clear Green Magenta Red
	Υ	Yellow	Υ	Yellow

Current Consumption

Version:		Voltage:	Current (per beacon):
12V dc		10-14V dc	750mA
24V dc		20-28V dc	300mA
48V dc		42-54V dc	180mA
115V ac	50Hz/60Hz	+/-10%	140mA
230V ac	50Hz/60Hz	+/-10%	55mA