HMCA112-05 Electronic Siren, Buzzer, Claxon & Bell



Applications and users that have traditionally demanded conventional electromechanical claxons, sirens, buzzers and bells can now choose the next generation alternative.

The E2S Hootronic series of products faithfully reproduce the sounds made by legacy electromechanical signalling devices but in a modern, reliable and cost effective way. With output levels of up to 122dB(A) at 1 metre the HMCA112-05 surpasses legacy electromechanical devices in performance and effectiveness, it is also continuously rated, requires zero maintenance and the signal quality will not degrade with age.

Features

The products in the Hootronic range have 5 user selectable 'traditional' sounds including:

- Tone 1 : Industrial Claxon
- Tone 2 : High Frequency Mechanical Siren
- Tone 3 : Medium Frequency Mechanical Siren
- Tone 4 : Electro Mechanical Buzzer
- Tone 5 : Mechanical Bell

Each of these sounds have two additional, remotely selectable, alarm stages.

Remote switch generates genuine 'tail off' to sound when alarm is terminated.


- Automatic synchronisation on multi-sounder system.
- Continuously rated.
- Large termination area.
- Stainless steel fixings.
- Ratchet adjustable stainless steel 'U' bracket for 360° positioning.
- Duplicate cable terminations (in & out for daisy-chain installations).
- Tropicalisation available on request.

💁 CE FAI

Approvals

• GOST-R certificate: POCC GB.JB05.H00144





Specification

cd:

cd:

Weight:

optimum voltage.

Hootronic Sounder:

1 Nominal output: 122dB(A) @ 1m +/- 3dB [113dB(A) @ 10ft/3m] 2 5 No. of tones: 1 No. of stages: 3 2 Volume control: Max. 122dB(A); Min. 113dB(A) approx. [> Beacon: 5 Joules (5Ws) Energy: Flash rate: 1Hz (60 fpm) Peak Candela: 500,000 cd - calculated from energy (J) Effective Intensity 250 cd - calculated from energy (J) Peak Candela: 16,428 cd* - measured ref. to I.E.S. Effective Intensity 51 cd* - measured ref. to I.E.S. Amber, Blue, Clear, Green, Red & Yellow Lens colours: Tube life: Emissions are reduced to 70% after 8 million flashes Xenon Beacon General: Voltages DC: 12 V dc; 2 4 V dc Voltages AC: 115V ac; 230V ac Ingress protection: IP66 & IP67 (Third party tested) Housing material: High impact UL94 VO & 5VA FR ABS Colour: Grey (RAL7038) Cable entries: 2 x M20 supplied with 1 blanking plug Lens material: Borosilicate glass dome with PC prismatic lens cover. Guard: Stainless Steel dome guard as standard Terminals: 0.5 to 4.0mm² cables. -25 to +55°C [-13° to +131°F] Operating temp: -40 to +70°C [-40° to +158°F] Storage temp: Relative humidity: 90% at 20°C [68°F]

DC: 3.00kg/6.6lbs AC:3.50kg/7.7lbs I*Candela measurements representative of performance with clear lens at

*SPL data +/-3dB(A). Measured at optimum voltage.

Version	Part code:
12Vdc	HMCA11205DC12G-xx
2 4V dc	HMCA11205DC24G-xx
115V ac	HMCA11205AC115G-xx
2 30V ac	HMCA11205AC230G-xx
[xx] = Lens colour:	AM: Amber, BL: Blue, CL: Clear, GN: Green, RD: Red, YW: Yellow

Alarm Sounder

Part Codes

V

Version: 2 4V dc			Current: 375mA*	
115V ac	50/60Hz	+/-10%	160mA	
2 30V ac	50/60Hz	+/-10%	75mA	
* current at no	ominal voltage			

_	Version: 12V dc		Wattage: 10-14V dc	Current: 550mA
	2 4V dc		2 0-2 8V dc	300mA
-	115V ac	50/60Hz	+/-10%	140mA
-	2 30V ac	50/60Hz	+/-10%	55mA

Tone table

S 1	Description	S 2	S 3
Τ1	Industrial Claxon	Т3	Т5
T 2	High Frequency Mechanical Siren	Τ1	T 5
Т3	Medium Frequency Mechanical Siren	Τ1	T 5
Τ4	Electro Mechanical Buzzer	T 2	T 5
Т5	Mechanical Bell	Τ1	T 2